
USER GUIDE MAGNETIC STRIP LIGHT



iTECHWORLD



CONTENTS

1.	Product Overview Overview Key Features Package Contents Unit Diagram	3 3 3 4
2.	Getting Started Operation Guide	5
3.	Charging Time & Power Display	5
4.	Specifications Maintenance	6
5.	Safety Precautions	6
6.	Contact Us	8

ITECHWORLD

OVFRVIFW

The iTechworld Magnetic Strip Light offers simple, user-friendly controls that allow you to easily cycle through the various lighting modes. From an amber light to deter insects and an SOS light for emergencies, the iTechworld Magnetic Strip Light is adaptable to any situation. Its compact size and lightweight design make it easy to carry, while an integrated hanging loop and dual magnets allow you to suspend it almost anywhere for hands-free lighting.

KEY FEATURES

- IP65 water registant
- Amber light to deter insects
- SOS omorgopey light
- In-built power bank
- Pro-installed magnets
- Lanvard loop
- Ultra-bright 300 Lumen

Package Contents



ITECHWORLD












UNIT DIAGRAM





- 1 LANYARD TIE POINT
- 6 USB-C INPUT PORT
- (2) TORCH LIGHT
- 7 POWER CONTROL
- (3) LIGHT DIFFUSER (4) BATTERY LEVEL INDICATOR
- 8 USB OUTPUT PORT (9) WATER RESISTANT COVER
- (5) STRONG MAGNETS

iTECHWORLD

GETTING STARTED

OPERATION

- Pressing the power button located at the end of the unit will change the lighting mode from the first white light to the second, then the third, then the SOS light and finally, the amber light.
- While the unit is off, holding the power button for over 2 seconds will turn on the torch light. A short or long press from this stage will turn off the light.
- When any light is on, holding the power button will turn off the light.

Operation	Light Mode	Brightness Level
Short Press	1st White Light	3%
2nd Short Press	2nd White Light	50%
3rd Short Press	3rd White Light	100%
4th Short Press	SOS Light	100%
5th Short Press	Amber Light	100%
Hold the Button	Torch Light	100%

CHARGING TIME & POWER DISPLAY

Using the included 5V/2.1A adaptor, the light will take around four hours to go from 0% to 100%. The device has four charge LED indicators that allow you to monitor

WHILE CHARGING

Display				
State of Charge	LEDs			
Full Charge	All LEDs will be on			
75% ~ Full	One LED will flash			
50% ~ 75%	One LED will flash, one is off			
25% ~ 50%	One LED will flash, two are off			
Flat ~ 25%	One LED will flash, the rest will be off			

ITECHWORLD

WHILE NOT CHARGING

Display				
State of Charge	LEDs			
75% ~ Full	All LEDs will be on			
50% ~ 75%	One LED will be off			
25% ~ 50%	Two LEDs will be off			
3% ~ 25%	Three LEDs will be off			
Flat ~ 3%	All LEDs will be off, one will flash			

SPECIFICATIONS

iTechworld Mini Magnetic Strip Light				
USB Output	5V/2.4A			
USB-C Input	5V/2.1A			
Power	3W Max			
Brightness	300LM			
Weight	0.330kg			
Charging Time	4 Hours			
Operating Temperature	0°C ~ 50°C			
Storage Temperature	-10°C ~ 60°C			
IP Rating	IP65			
Dimensions (LxWxH)	35 x 35 x 292mm			

MAINTENANCE

Wipe the product and its surfaces down using a soft, dry cloth. Do not use liquids or solvents which will damage the product's surface.

SAFETY PRECAUTIONS

For safe operation, the iTechworld Magnetic Strip Light must be operated correctly. Please carefully read, understand, and follow all instructions in this user guide. Failure to follow these instructions may result in damage to the unit or property, death or serious injury.

Disclaimer: While iTechworld has taken every precaution to ensure the accuracy of the contents of this user guide, iTechworld assumes no responsibility for any errors or omissions.

Furthermore, all specifications and functionality may change at any time

It is best to view our website for the most up-to date information

Should any of the following occur, immediately turn off and stop using the unit:

- Any liquid, including water, spills into the product
- The product gives off odours or has an unusual flickering.
- The cable is damaged, or you can see the exposed wire.

WARNING:

Keep all components of this device away from fires and high temperatures.

WARNING

Keep all components of this device away from children.

WARNING: Check the voltage requirements before operation to avoid damage to the light.

WARNING

Do not disassemble or modify the light; doing so may result in a risk of death or serious injury and will void your warranty.

WARNING Ensure the light is charged at least once every three months and is not left out of

charge (0%) for more than seven days.

Unplug the power cord once the light has been fully charged (100%).

WARNING:

Do not cover the light while the unit is in operation.

ITECHWORLD

iTECHWORLD

CONTACT US

1300 483 249

service@itechworld.com.au

www.itechworld.com.au

When it comes to energy storage and creation at iTechworld, we take pride in being one of the biggest names in the industry. Based in Australia, we are a family-owned and operated business. With many more innovative products on the horizon we are committed to constantly raising the bar to provide bigger and better benefits to all our customers Australia wide

Whether you're an avid camper, 4WD enthusiast, freedom seeker or camper, we've got your power needs covered. Escape the grid without compromise, minimise your downtime and travel with comfort with our large range of leading products at great prices.


iTechworld The Power Expert

LOVE YOUR MAGNETIC STRIP LIGHT? LEAVE A REVIEW













ITECHWORLD